

CERTIFICATE of Conformity



Registration No.: A3 50687813 0001

Report No.: CN25FUFC 001

Holder: **Wanbang Digital Energy Co., Ltd.**
No.39 Longhui Road, Wujin High-tech
Zone, Changzhou,
Jiangsu
P.R. China

Product: **EV Charging System**
(DC WALLBOX)

Identification: Type Designation : AD20110EU1995
Firmware Version : V3.9.0
Remark(s) : Refer to report CN25FUFC 001 for details.


Tested acc. to: EN 50549-1:2019+A1
EN 50549-10:2022

The certificate of conformity refers to the above mentioned product. This is to certify that the specimen is in conformity with the assessment requirement mentioned above. This certificate does not imply assessment of the production of the product and does not permit the use of a TÜV Rheinland mark of conformity.

Date 06.08.2025

Durch die DAKKS nach
DIN EN ISO/IEC 17065:2013
akkreditierte Zertifizierungsstelle.
Die Akkreditierung gilt nur für den in der
Urkundenanlage D-ZE-14169-01-02
aufgeführten Akkreditierungsumfang.

Certification Body


Bowen Dong

TÜV Rheinland LGA Products GmbH - Tillystraße 2 - 90431 Nürnberg

Certificate No.: A3 50687813 0001

Certificate Of Conformity

License holder: **Wanbang Digital Energy Co., Ltd.**
No.39 Longhui Road, Wujin High-tech Zone, Changzhou, Jiangsu P.R. China

Type of product: EV Charging System (DC WALLBOX)

Model: AD20110EU1995

Firmware version: V3.9.0

Standard: **EN 50549-1:2019+A1**
Requirements for generating plants to be connected in parallel with distribution networks - Part 1: Connection to a LV distribution network -Generating plants up to and including Type B
EN 50549-10:2022
Requirements for generating plants to be connected in parallel with distribution networks - Part 10: Tests for conformity assessment of generating units

Report No.: CN25FUFC 001

Date of issue: 06.08.2025

The verification of conformity refers to the above mentioned product. This is to verify that the specimen is in conformity with the assessment requirement mentioned above. This verification does not imply assessment of the production of the product and does not permit the use of a TÜV Rheinland mark of conformity.



Page 1 of 6

EN 50549-1:2019+A1 Annex C Parameter Table

Clause(s) / sub-clause(s) of EN 50549-1:2019+A1	Parameter ^a	Remarks / additional information ^b	Typical value range	Value default	
4.4.2 Operating frequency range	47,0 – 47,5 Hz Duration	Unlimited	0 – 20 s	0s	
	47,5 – 48,5 Hz Duration	Unlimited	30 – 90 min	30 min	
	48,5 – 49,0 Hz Duration	Unlimited	30 – 90 min	30 min	
	49,0 -51,0 Hz Duration	Unlimited	not configurable	unlimited	
	51,0 – 51,5 Hz Duration	Unlimited	30 – 90 min	30 min	
	51, 5 – 52 Hz Duration	Unlimited	0 – 15 min	0 s	
4.4.3 Minimal requirement for active power delivery at underfrequency	Reduction threshold	Not configurable	49 Hz – 49,5 Hz	49,5 Hz	
	Maximum reduction rate	No reduction ($\leq 10\% P_M / \text{Hz}$)	2– 10 % PM/Hz	$\leq 2\% \text{ PM/Hz}$	
4.4.4 Continuous operating voltage range	Upper limit	110% U_c	not configurable	110% U_n	
	Lower limit	85% U_c	not configurable	85% U_n	
4.5.2 Rate of change of frequency (ROCOF) immunity	ROCOF withstand capability (defined with a sliding measurement window of 500 ms)	Up to $\pm 3.5 \text{ Hz/s}$	not defined	$\pm 2 \text{ Hz/s}$	
4.5.3.2 Generating plant with non-synchronous generating technology	Maximum power resumption time	Not configurable	not defined	1 s	
	Voltage-Time-Diagram	Configurable (Default / Most stringent requirement)	see Figure 6	Time [s]	U [p.u.]
				0,0	0,2
				0,15	0,2
4.5.4 Over-voltage ride through (OVRT)	Voltage-Time-Diagram	Configurable (Default requirement)	not configurable	1,5	0,85
				1 s	
				Time [s]	U [p.u.]
				0,0	1,25
				0,1	1,25
				0,1	1,20
				5,0	1,20
4.5.5 – Phase jump immunity	Phase jump immunity	Not configurable (Up to $\pm 180^\circ$)	Not configurable	5,0	1,15
				5,0	1,15
				60	1,10
				$\pm 180^\circ$	

4.6.1 Power response to over frequency	Threshold frequency f_1	Configurable	50,2 Hz – 52 Hz	50,2 Hz
	Droop	Configurable	2 % – 12 %	5 %
	Power reference	Configurable	PM P _{max}	P _{max} , for synchronous generating technology and EESS
	Intentional delay	Configurable	0 – 2 s	0s
	Deactivation threshold f_{stop}	Configurable	50,0 Hz – f_1	deactivated
	Deactivation time t_{stop}	Configurable	0 – 600 s	-
	Acceptance of staged disconnection	Not configurable	yes no	yes
4.6.2 Power response to underfrequency	Threshold frequency f_1	Configurable	49,8 Hz – 46 Hz	49,8 Hz
	Droop	Configurable	2 – 12 %	5 %
	Power reference	Not configurable (P _{max})	PM P _{max}	P _{max}
	Intentional delay	Configurable	0 – 2 s	0 s
4.7.2.2 Capabilities	Active factor / Reactive power (%Pd) range overexcited	0,9 – 1 / 44% P _n – 0	0,9 – 1 / 48 %Pd - 0 0,95 – 1 / 33 %Pd - 0	0,9 – 1 / 44% P _n – 0
	Active factor / Reactive power (%Pd) range underexcited	0,9 – 1 / -44% P _n – 0	0,9 – 1 / 48 %Pd - 0 0,95 – 1 / 33 %Pd - 0	0,9 – 1 / -44% P _n – 0
4.7.2.3 Control modes	Enabled control mode	Configurable	Q setp. Q(U) Q(P) cos ϕ setp. cos ϕ (P)	Q setpoint
4.7.2.3.2 Setpoint control modes	Q setpoint and excitation	Configurable	0 – 48 % PD, 0 – 33 %PD	0
	Cos ϕ set point and excitation (ov and uv)	Configurable	1 – 0,9	1
	Time constant (τ)	Configurable (3 – 60 s)	3s-60s	3,33s



4.7.2.3.3 Voltage related control modes	Characteristic curve	Configurable $Q(U)$	D_{bchar} : -6% to +6 % U_n $Q_{max char}$: 10% – 100% of $Q_{max over}$ and $Q_{max under}$ Slope of the steepest: 1% – 100% $Q_{max} / 1\%$ U_n	indicate default characteristic (Figure 33 of EN 50549-10)
	Time constant (τ)	Configurable (3 s – 60 s)	3 s – 60 s	3,33 s
	Min cos φ	Configurable	0,0 – 1	0,9
	Lock in power(P/P_n)	Configurable	0 % – 20 %	deactivated
	Lock out power(P/P_n)	Configurable	0 % – 20 %	deactivated
4.7.2.3.4 Power related control mode	Characteristic curve	Configurable Cos φ (P) $Q(P)$	$Q_{max char}$: 10% – 100% of $Q_{max over}$ and $Q_{max under}$ Slope of the steepest: 2% – 200% $Q_{max} / 10\%$ P_n	indicate default characteristic (Figure 36 of EN 50549-10)
	Time constant (τ)	Configurable	3 s – 60 s	3,33 s
	Lock-in voltage (U/U_n)	Configurable	100% – 110%	deactivated
	Lock-out voltage (U/U_n)	Configurable	90% – 100%	deactivated
4.7.4.2.2 Zero current mode for converter connected generating technology	Enabling	Configurable	enable disable	disabled
	Static voltage range overvoltage	Configurable	100 % U_n – 120 % U_n	120 % U_n
	Static voltage range undervoltage	Configurable	20 % U_n – 100 % U_n	50 % U_n

4.9.2 Requirements on voltage and frequency protection	Threshold for protection as dedicated device [in A or kW, kVA]	Configurable	16 A – 250 kVA	
	Undervoltage threshold stage 1	Configurable	0,2 Un – 1 Un	
	Undervoltage operate time stage 1	Configurable	0,1 s – 100 s	
	Undervoltage threshold stage 2	Configurable	0,2 Un – 1 Un	
	Undervoltage operate time stage 2	Configurable	0,1 s – 5 s	
	Overvoltage threshold stage 1	Configurable	1,0 Un – 1,2 Un	
	Overvoltage operate time stage 1	Configurable	0,1 s – 100 s	
	Overvoltage threshold stage 2	Configurable	1,0 Un – 1,3 Un	
	Overvoltage operate time stage 2	Configurable	0,1 s – 5 s	
	Overvoltage threshold 10 min mean protection	Configurable	1,0 Un – 1,15 Un	
	Underfrequency threshold stage 1	Configurable	47,0 Hz– 50,0 Hz	
	Underfrequency operate time stage 1	Configurable	0,1 s – 100 s	
	Underfrequency threshold stage 2	Configurable	47,0 Hz – 50,0 Hz	
	Underfrequency operate time stage 2	Configurable	0,1 s – 5 s	
	Overfrequency threshold stage 1	Configurable	50,0 Hz – 52,0 Hz	
	Overfrequency operate time stage 1	Configurable	0,1 s – 100 s	
	Overfrequency threshold stage 2	Configurable	50,0 Hz – 52,0 Hz	
	Overfrequency operate time stage 2	Configurable	0,1 s – 5 s	



4.10.2 Automatic reconnection after tripping	Lower frequency	Configurable	47,0 Hz – 50,0 Hz	49,5 Hz
	Upper frequency	Configurable	50,0 Hz – 52,0 Hz	50,2 Hz
	Lower voltage	Configurable	50 % Un – 100 % Un	85 % Un
	Upper voltage	Configurable	100 % Un – 120 % Un	110 % Un
	Observation time	Configurable	10 s – 600 s	60 s
	Active power increase gradient	Configurable	6 % – 3000 %/min	10 % /min
4.10.3 Starting to generate electrical power	Lower frequency	Configurable	47,0 Hz – 50,0 Hz	49,5 Hz
	Upper frequency	Configurable	50,0 Hz – 52,0 Hz	50,1 Hz
	Lower voltage	Configurable	50 % – 100 % Un	85 % Un
	Upper voltage	Configurable	100 % – 120 % Un	110 % Un
	Observation time	Configurable	10 s – 600 s	60 s
	Active power increase gradient	Configurable	6 % – 3000 %/min	disabled
4.11.1 Ceasing active power	Remote operation of the logic interface	Configurable	yes no	No (Digital input by dry contact)
4.11.2 Reduction of active power on set point	Remote operation NOTE: If yes further definition is provided by the DSO	Configurable	yes no	No (Digital input by dry contact)
4.12 Remote information exchange	Remote information exchange required NOTE: If yes further definition is provided by the DSO	Configurable	yes no	No (The protocols will be agreed between the local DSO and PGUs at final installation.)
Supplementary: <i>Complémentaire</i> ov: Over-excited; uv: Under-excited ^a If additional parameters have been evaluated during the test, these shall be added as additional lines in the table. ^b This column should be used for manufacturer specific parameter descriptions.				

